

# CLEVO<sup>®</sup>



## D900C

Professional laptop with super-engine



## D900C

CPU	<ul style="list-style-type: none"> <li>Intel<sup>®</sup> Core 2 Duo Processor E6300/E6400 (1.86/2.13GHz, 65nm, FSB1066, 2MB L2 cache, LGA775)</li> <li>Intel<sup>®</sup> Core 2 Duo Processor E6600/E6700 (2.4/2.67GHz, 65nm, FSB1066, 4MB L2 cache, LGA775)</li> <li>Intel<sup>®</sup> Core 2 Duo Processor E6550/E6850 (2.33/3.0GHz, 65nm, FSB1066/FSB1333, 4MB L2 cache, LGA775)</li> <li>Intel<sup>®</sup> Core 2 Quad Processor Q6600/Q6700 (2.4/2.66GHz G0 Stepping 65nm, FSB1066, 8MB L2 cache, LGA775)</li> <li>Intel<sup>®</sup> Core 2 Extreme Processor X6800 (2.93GHz, 65nm, FSB1066, 4MB L2 cache, LGA775)</li> </ul>			
Core Logic	Intel <sup>®</sup> P965 + ICH8-R			
Display	17.1" with Glare Type WXGA (1440x900) / 17.1" WSXGA+ (1680x1050) / 17.1" WUXGA (1920x1200) TFT LCD			
Memory	<ul style="list-style-type: none"> <li>64-bit wide DDRII data channel</li> <li>Two 200pin SODIMM sockets, supporting DDRII 533/667/800</li> <li>Expandable Memory up to 4GB, available, based on 512/1024/2048MB SODIMM Module</li> </ul>			
Video Controller	<ul style="list-style-type: none"> <li>nVIDIA<sup>®</sup> GeForce<sup>®</sup> Go 7950GTX, MXM-IV Modular</li> <li>XP &amp; VISTA SLI ready</li> <li>512MB GDDRIII Video RAM on board, support PCI-E*16</li> <li>MS DirectX<sup>®</sup> 9 Compatible</li> </ul>	<ul style="list-style-type: none"> <li>nVIDIA<sup>®</sup> GeForce<sup>®</sup> 8700M GT, MXM-IV Modular</li> <li>512MB GDDRIII Video RAM on board, support PCI-E*16</li> <li>MS DirectX<sup>®</sup> 10 Compatible, HDCP support</li> <li>XP &amp; VISTA SLI ready</li> </ul>	<ul style="list-style-type: none"> <li>nVIDIA<sup>®</sup> Quadro<sup>®</sup> FX 1600M, MXM-IV Modular</li> <li>512MB GDDRIII Video RAM on board, support PCI-E*16</li> <li>MS DirectX<sup>®</sup> 10 Compatible, HDCP support</li> </ul>	<ul style="list-style-type: none"> <li>nVIDIA<sup>®</sup> GeForce<sup>®</sup> 8800M GTX, MXM-IV Modular</li> <li>512MB GDDRIII Video RAM on board, support PCI-E*16</li> <li>MS DirectX<sup>®</sup> 10 Compatible, HDCP support</li> </ul>
Storage	<ul style="list-style-type: none"> <li>1x changeable 12.7mm(H) Combo/DVD-Dual</li> <li>3x changeable 9.5mm(H), SATAII HDD(5400RPM/7200RPM RAID 0/1/5 support)</li> <li>(Option) Blu-Ray Readable / Writable drive</li> <li>(Option) HD-DVD Readable / Writable drive</li> <li>(Option) 1x external USB 1.44MB Floppy Disk Drive</li> </ul>			
Keyboard	<ul style="list-style-type: none"> <li>Full size keyboard with Numeric pad, Multi-Language support</li> <li>Built-in Touchpad with scrolling function</li> </ul>			
Sound System	<ul style="list-style-type: none"> <li>UAA (Universal Audio Architecture)</li> <li>Integrated Azalia compliant interface</li> <li>S/PDIF Digital output</li> <li>1x Built-in Microphone</li> <li>4x Built-in Speakers</li> </ul>			
I/O Ports	<ul style="list-style-type: none"> <li>4x USB 2.0 ports</li> <li>1x Mini IEEE 1394a port</li> <li>1x S-Video out jack for TV output &amp; HDTV output</li> <li>1x External CRT monitor output</li> <li>1x DVI output (support DVI-Dual Link)</li> <li>1x Headphone jack</li> <li>1x Microphone jack</li> <li>1x S/PDIF output jack</li> <li>1x RJ-45 jack for 10M/100M Fast Ethernet</li> <li>1x RJ-11 jack for Plug &amp; Play Fax/Modem</li> <li>1x Line-in jack for Audio input</li> <li>1x DC-In jack</li> <li>1x CATV input jack (Functional option with TV-Tuner module)</li> <li>1x S-Video in jack for Internal TV-Tuner (Functional option with TV-Tuner module)</li> </ul>			
Slots	<ul style="list-style-type: none"> <li>1x New Card (34/54 pin) socket (support USB&amp;PCI-E interface)</li> <li>1x Mini-card socket (support USB&amp;PCI-E interface), it's for WLAN</li> <li>1x Mini-PCI socket, for TV-Tuner module</li> <li>Embedded 7-in-1 Card Reader (MS/MS Pro/MS Duo/MS Pro Duo/SD/Mini-SD/MMC)</li> </ul>			
Communication	<ul style="list-style-type: none"> <li>56K MDC Azalia Modem with V.90 &amp; V.92 compliant</li> <li>Gigabit LAN on board</li> <li>(Option) Intel<sup>®</sup> Wireless/Pro 3945ABG</li> <li>(Option) Intel<sup>®</sup> Wireless WiFi Link 4965AGN</li> <li>(Option) Bluetooth ClassII V2.0, USB interface</li> <li>(Factory Option) 1.3M/2.0M pixel video camera module</li> </ul>			
Power	<ul style="list-style-type: none"> <li>Full Range 220W AC adapter - AC input 100~240V, 47~63Hz, DC output 20V, 11A</li> <li>Main battery changeable 12-cell smart Li-Ion pack, 6600mAh</li> </ul>			
Security	Kensington <sup>®</sup> Lock			
O.S.	<ul style="list-style-type: none"> <li>Windows<sup>®</sup> XP</li> <li>Windows<sup>®</sup> VISTA Premium</li> </ul>			
Dimension	<ul style="list-style-type: none"> <li>397(W) x 298(D) x 51~60(H)mm</li> <li>5.4Kg with 12 cells Battery</li> </ul>			
Options	<ul style="list-style-type: none"> <li>DVD Dual drive module</li> <li>Wireless LAN (Mini-card) module, PCI-E interface</li> <li>Bluetooth module, USB interface</li> <li>Blu-Ray &amp; HD-DVD Drive Module</li> <li>TV-Tuner module, Mini-PCI interface</li> <li>(Factory Option) 1.3M/2.0M pixel video camera module, USB 2.0 interface</li> </ul>			

\*\* Battery Life may vary depending on applications and configuration.

The specifications in gray are not available yet.

The content is subject to change without notice. Other brand and product names are trademarks and/or registered trademarks of their respective companies.