











Having docking station is much more convenient and easier. With dedicated docking station, your T5100/T5110 laptop can extend to personal periperals within few seconds.



	DS101
Keyboard and Pointing Device	. Power button
	. NB Eject button
	. Docking lock switch
	. 7x USB 2.0 ports
	. 1x external VGA port
I/O ports	. 1x DVI-D ouput port
	. 1x Headphone jack
	. 1x Microphone jack
	. 1x S/PDIF output jack
	. 1x RJ-45 LAN port
	. 1x RS232
	. 1x Docking port
	. 1x DC-in jack
Power Supply	. Full Range AC adapter 90W, AC in 100~240V, 50~60Hz, DC output 19V/4.74A
Security	. Kensingten Lock
Indicators	. LED indicators (Adapter power / system operating indicator, Lock switch indicator)
Certificate	. Eup
Environmental Specifications	. Operating Temperature: 5 °C ~ 35 °C
	. Non-Operating Temperature: -20 °C ~ -60 °C
	. Operating Relative Humidity: 20% ~ 80%
	. Non-Operating Relative Humidity: 10% ~90%
Dimension	. 300(W) x 195(D) x 39.5(H) mm
Weight	. 634g

\*\* Battey Life may vary depending on applications and configuration.

The content is subject to change without notices. Other brand and product names are trademarks and /or register trademarks of their respective companies.